

Device: 7SJ82 Overcurrent protection

Product code

Short: P1J1809053
Long: 7SJ82BAAAAA00AAAA0AE041112113BAAA000000AB0HB1BD4JA0



Technical Data:

Firmware:	Current version
Binary inputs:	23
Binary outputs:	16 Relays (16 Standard, 0 Fast, 0 High-Speed, 0 Power)
Current transformers:	4 for protection
Voltage transformers:	4 standard
Measuring-transducer inputs:	0 (20 mA or 10 V, fast) 0 (20 mA, standard) 0 (DC 300 V) 0 (20 mA, fast) 0 (temperature)
Housing width:	1/3 x 19"
Housing type:	Flush mounting
Modules in 19" row 1:	IO102, PS101, IO110
LEDs/Push-buttons:	16 LEDs
Operation Panel:	Integrated
Key switch:	Without
Display type:	Small display
Front Design:	Standard
Power Supply:	DC 110 V-250 V, AC 100 V-230 V

Communication/Plug-in modules:

Communications encryption:	Normal
Integrated Ethernet port J:	DIGSI 5 and IEC 61850/Goose
Plug-in module position E:	ETH-BA-2EL: 2x electric Ethernet 100 Mbit/s, RJ45 Communication Protocols: applicable for DIGSI 5, IEC 61850-8-1 MMS and GOOSE, IEC 60870-5-104, DNP3 TCP, Modbus TCP, Synchrophasor (IEEE C37.118 - IP), Profinet IO, SUP, DHCP, SNTP, SNMP, etc. Redundancy protocols: Line Mode, RSTP, HSR, PRP
Plug-in module position F:	Port is available but not assembled

Functions:

Function points class:	Base + 40 function points
------------------------	---------------------------

Note on function-points class

The function-points class results from the sum of the function points of the selected functions. You can apply these functions according to the selected function-points class. The device also allows each other selection of functions if the sum of the required function points is within the selected function-points class.

From Version V9.3 on the function-points class "1400+" is withdrawn. With this class function-points exceeding the limit of 1400 were free of charge. The maximum function-points class is now 1400. If a function-points budget of more than 1400 points is required for a device the application Function-Point-Manager need to be applied. All function points are liable to cost.

In the engineering phase DIGSI 5 checks that the selected configuration is suitable (capable of running in the device) before loading it to the device.

Miscellaneous:

Warranty:	2 years
Special Approvals:	Without
Firmware:	Current version

7SJ82 Overcurrent-Time Protection - Overview Function points calculation

(P1J1809053)

Functions Free of Charge

ANSI	Function	Abbr.	Included
	Protection functions for 3-pole tripping	3-pole	✓
37	Undercurrent	$I <$	✓
38	Temperature supervision	$\theta >$	✓
46	Negative-sequence overcurrent protection	$I_2 >$	✓
46	Unbalanced-load protection (thermal)	$I_2^2 t >$	✓
49	Thermal overload protection	$\theta, I^2 t$	✓
49	Thermal overload protection, user-defined characteristic	$\theta, I^2 t$	✓
	Instantaneous tripping at switch onto fault	SOTF	✓
50HS	Instantaneous high-current tripping	$I >>>$	✓
50/51 TD	Overcurrent protection with positive-sequence current I_1 (from V7.9)	$I_1 >$	20 X ✓
50N/ 51N TD	Overcurrent protection, ground	$I_N >$	✓
50N/ 51N TD	Overcurrent protection, 1-phase	$I_N >$	✓
50Ns/ 51Ns	Sensitive ground-current detection for systems with resonant or isolated neutral systems incl. a) $3I_0 >$, b) admittance $Y_0 >$, c) $3I_0\text{-harm} >$ (from V7.8)	$I_{Ns} >$	✓
74TC	Trip-circuit supervision	TCS	✓
74CC	Closed-circuit supervision (from V7.9)	CCS	✓
86	Lockout		✓
AFD	Arc-protection (only with plug-in module ARC-CD-3FO)		5 X ✓
	Measured values - standard		✓
	Switching statistic counters		✓
	PQ-Basic measured values: THD (Total Harmonic Distortion) and harmonics (from V8.01) THD voltage aggregation values (from V8.40)		✓

	CFC (Standard, control)		✓
	Switching sequences function		20 X ✓
	Inrush current detection		✓
	External trip initiation		✓
	Control		✓
	Protection interface, serial		✓
	Monitoring and supervision		✓
	Fault recording of analog and binary signals		✓
	Frequency-tracking groups (from V7.8)		6 X ✓
	Temperature acquisition via communication protocol		✓

Functions with Costs

ANSI	Function	Abbr.	Included	Quantity	Value	Points
24	Overexcitation protection	V/f		1	25	25
25	Synchrocheck, synchronization function	Sync		0	50	0
25	Synchronization function with balancing commands, 1 channel for each sync. location	Sync		0	80	0
27	Undervoltage protection: "3-phase" or "positive-sequence system V1" or "universal Vx"	V<		1	5	5
27R, 59R	Rate-of-voltage-change protection (from V8.30)	dV/dt		0	5	0
	Undervoltage-controlled reactive power protection	Q>/V<		0	15	0
32, 37	Power protection active/reactive power	P<>, Q<>		0	10	0
32R	Reverse-power protection	- P<		1	5	5
46	Negative-sequence overcurrent protection with direction			0	10	0

47	Overvoltage protection: "negative-sequence V2" or "negativ-sequence V2/positiv-sequence V1"	$V2>; V2/V1>$		0	5	0
49	Thermal overload protection for RLC filter elements of a capacitor bank	θ, I^2t		0	10	0
50/51 TD	Overcurrent protection, phases	$I>$	2 X ✓	2	30	0
50/51 TD	Overcurrent protection for RLC filter elements of a capacitor bank	$I>$		0	10	0
	Ground-fault detection via pulse pattern detection; Note: this stage additionally requires the function 50Ns/51Ns or 67Ns "Sensitive ground-fault detection for systems with resonant or isolated neutral"	IN-pulse		0	15	0
	Intermittent ground-fault protection	lie>		0	20	0
50BF	Circuit-breaker failure protection, 3-pole	CBFP		0	5	0
50RS	Circuit-breaker restrike protection	CBRS		0	20	0
51V	Overcurrent protection, voltage dependent	$t=f(I,V)$		0	10	0
59, 59N	Overvoltage protection: "3-phase" or "zero-sequence system V0" or "universal Vx"	$V>$		1	5	5
59C	Peak overvoltage protection, 3-phase, for capacitors	$V>$ cap.		0	30	0
59NU	Neutral-point Voltage-Unbalance Protection (from V8.6)	UNU>		0	30	0
60	Voltage-comparison supervision	$\Delta U>$		0	5	0
60C	Current-unbalance protection for capacitor banks	$I_{unbal}>$		0	50	0
67	Directional overcurrent protection, phases			0	15	0
67N	Directional overcurrent protection, ground			0	15	0

67Ns	Dir. sensitive ground-fault detection for systems with resonant or isolated neutral incl. a) $3I_0>$, b) $V_0>$, c) $\cos/\sin\Phi$, d) Transient ground-fault fct., e) $\Phi(V,I)$, f) admittance			0	30	0
	Directional stage with a harmonic; Note: this stage additionally requires the function "67Ns Dir. sensitive ground-fault detection for systems with resonant or isolated neutral"			0	10	0
	Directional intermittent ground-fault protection	lie dir>		0	20	0
79	Automatic reclosing, 3-pole	AR		0	35	0
81	Frequency protection: "f>" or "f<" or "df/dt"	f<>; df/dt<>		0	5	0
81U	Underfrequency load-shedding	f<(UFLS)		0	15	0
	Vector-jump protection	$\Delta\phi>$		0	20	0
87N	Restricted ground-fault protection	ΔI_N		0	15	0
87C	Differential protection, capacitor bank	ΔI		0	95	0
90V	Automatic voltage controller for two-winding transformer			0	150	0
90V	Automatic voltage controller for two-winding transformer with parallel operation			0	180	0
	Number of two-winding transformers with parallel operation (Note: only together with the function "Automatic voltage controller for two-winding transformer with parallel operation")		2 X ✓	2	5	0
FL	Fault locator, single-sided	FL-one		0	25	0
FL	Fault locator plus (from V7.9)	FL plus		0	45	0
PMU	Synchrophasor measurement	PMU		0	40	0
	Measured values - extended: Min, Max, Avg			0	3	0
	PQ-Basic measured values: Voltage unbalance (from V8.40)			0	20	0

	PQ-Basic measured values: Voltage variations - voltage dips, swells and interruptions (from V8.40)			0	30	0
	PQ-Basic measured values: TDD - Total Demand Distortion (from V8.40)			0	10	0
	CFC arithmetic			0	40	0
	Circuit-breaker monitoring (from V9.20)	ΣI_x , I^2t , 2P, tO, tC, pole scatter, discrepancy		0	10	0
	Disconnecter monitoring (from V9.50)	tO, tC		0	5	0
	Circuit-breaker		4 X ✓	4	3	0
	Disconnecter/Grounding switch		4 X ✓	4	3	0
	Multiplexing of protection interface			0	50	0
SSR	Slow-scan recorder (Mod.: from V8.80, Non-Mod.: from V9.40)	SSR	1 X ✓	1	40	0
CR	Continuous recorder (Mod.: from V9.20, Non-Mod.: from V9.40)	CR	1 X ✓	1	25	0
TR	Trend recorder (Mod.: from V9.30, Non-Mod.: from V9.40)	TR	1 X ✓	1	25	0
	Cyber Security: Role-Based Access Control (from V7.8)			0	25	0
	Cyber Security: IEEE 802.1x based network authentication (from V8.3)			0	10	0
27-CEI	Region Italy: undervoltage protection according to the CEI 0-16 standard (from V9.50)	V<		0	5	0
59-CEI	Region Italy: overvoltage protection according to the CEI 0-16 standard (from V9.50)	V>		0	5	0
81-CEI	Region Italy: frequency protection according to the CEI 0-16 standard (from V9.50)	f<>		0	10	0
Total:						40